

Calendar 13-2

- Opening Calendar 13-2
- Creating Calendar Events 13-2
- Saving Holidays/Memorial Days 13-3
- Viewing/Editing Calendar Event Details 13-4
- Calendar Functions 13-4

Tasks 13-5

- Saving a Task 13-5
- Using Tasks 13-6

Alarms 13-6

- Alarm Tone 13-6
- Setting Alarm 13-7

Calculator 13-8

Notepad 13-8

- Saving a Note 13-8
- Notepad Functions 13-9

Osaifu Keitai® 13-9

- Downloading Lifestyle-Appli 13-10
- Activating Lifestyle-Appli 13-10
- Reader/Writer Transactions 13-11
- IC Card Lock 13-12

Dictionary (Japanese) 13-13

Sound Recorders 13-14

- Voice Recorder 13-14
- Voice Announce 13-14

Bar Code Reader 13-15

- Scanning Barcodes 13-15
- Viewing/Editing Scanned Data 13-16
- Using Scanned Data 13-16

Calendar


View by day, week or month; set Alarms for events.

Opening Calendar

Main Menu ► Tools ► Calendar

Current month appears.

- When a date with Calendar events is selected, number of AM and PM events and up to three contents appear.
- Press [Prev.] or [Next] to show previous/next month calendar.
- To switch Monthly/Weekly view: P.13-4




Monthly View

Creating Calendar Events

Save up to 1000 entries.

Main Menu ► Tools ► Calendar

- 1 to highlight a date → [New] → *Schedule*



- 2 Select an item (See below)

Item	Operation/Description
Select icon/ Edit summary	> Select an icon → Edit subject
Edit location	> Enter location
Whole day setting	> OFF or ON ● When ON is set, Alarm goes off at 0:00 a.m.
Date (from)	> Enter start date and time
Date (to)	> Enter end date and time
Repeat	> Select a repeat type → (For Select day , check days → [Finish])
Alarm	> Select an Alarm type (→ For ON/Set time , enter time) ● Alarm Tone: P.13-6
Alarm tone	> Select an Alarm tone type → Select a folder → Select an Alarm tone
Contents	> Enter event description

3 [Finish]

Calendar Event Indicators

Following indicators appear in Calendar Window.

- (Blue): Morning event
- (Orange): Afternoon event
- (Underscore): Event that lasts for two days or longer
- Following indicators appear on Display.
 - : Alarm
 - : Monthly
 - : Daily
 - : Yearly
 - : Weekly

Note

- Calendar events between 00:00 on 2000/01/01 and 23:59 on 2037/12/31 can be saved on handset.
- Alarm tone does not sound when Privacy Key Lock or Personal Data Lock is set. However, settings can be changed even while Personal Data Lock is set (➡P.12-6).

Saving Holidays/Memorial Days

Save up to 100 entries (one entry a day) each for Holidays or Memorial days.

Main Menu ► Tools ► Calendar

- 1 (Highlight a date →) [New] → *Holidays* or *Memorial days*
- 2 Select an item (See below)

Item	Operation/Description
Date setting	> Enter a date
Repeat	> Select a repeat type <ul style="list-style-type: none">● 1 time does not repeat Holidays/Memorial days events.
Edit holiday/anniversary	> Enter description

3 [Finish]

Indicators

Holidays appear in red.

Memorial days are marked with a red circle.

- Following indicators appear in Calendar/Calendar Event List Window:
 - : Holidays
 - : Memorial days
 - : Yearly repeat

Viewing/Editing Calendar Event Details

Main Menu ► Tools ► Calendar


1  to select a date

2010/ 2/ 5(Fri)	
1	11:35~11:35 Scheduled
2	11:40~12:00 Shopping
3	12:30~13:00 Meal

Calendar Event List

2 Select an event

Detailed schedule appears.

- To edit:  [Edit] → Edit selected item (Schedule:  From Step 2 on P.13-2/ Holiday, Anniversary:  From Step 2 on P.13-3)


Schedule	
Summary	Scheduled
Whole day	OFF
Date(from)	2010/ 2/ 5(Fri) 11:35
Date(to)	2010/ 2/ 5(Fri) 11:35
Repeat	OFF
Alarm	OFF
Contents	Scheduled

Calendar Event Details




Calendar Functions

From ► Main Menu ► Tools ► Calendar


Functions Available in Calendar Window



> Highlight a date →  [Menu] → Select an item (See below)

Item	Operation/Description
New	Create a new entry ( P.13-2, P.13-3)

Item	Operation/Description
Weekly display/ 1 Month	Toggle Monthly/Weekly view
Icon display	Entries in category of selected icon appear > Select an icon
No. of schedules	Display number of saved Schedule, Holiday or Anniversary entries
Add shortcut icon	Create a shortcut ( P.1-25)
Send all Ir data	( P.11-3)
All IC transmission	( P.11-5)
Delete past	Delete past entries/items, prior to highlighted date > Select a category to delete → YES
Delete all	> Enter Phone Password → Select an item → YES
Reset holidays	Restore deleted Holidays > YES

Functions Available in Calendar Events List/Details

> Select a date (→ Select a Schedule, Holiday or Anniversary) →  [Menu] → Select an item (See below)

Item	Operation/Description
New	Create a new entry ( P.13-2, P.13-3)
Edit	Edit selected item ( Left)
Copy	Copy an entry to another day > Enter date and time to copy an entry to
Calendar display	Switch from Icon display to Calendar display

Item	Operation/Description
Icon display	Entries in category of selected icon appear > Select an icon
Set secret mode/ Release secret	Activate/deactivate Secret Mode > YES (→ For Set secret mode , enter Phone Password) ● Secret entries appear only in Secret Mode or Secret Data Only (↪P.12-10).
Compose message	Insert event date and details to message text (↪From Step 2 on P.14-4)
Send Ir data	(↪P.11-3)
Send all Ir data	(↪P.11-3)
IC transmission	(↪P.11-5)
AllIC transmission	(↪P.11-5)
Copy to microSD	Copy an entry to microSD Card > YES ● To display data on microSD Card: ↪P.10-20
Delete this	> YES
Delete past	Delete past entries/items, prior to highlighted date > Select a category to delete → YES
Delete select	> Check entries to delete → [Finish] → YES

Tasks

Make quick notes of task to manage in Task list.

Saving a Task

Main Menu ▶ Tools ▶ Tasks

- 1 [New] → Select an item (See below)
 - To check saved Tasks, select a Task. To edit, press [Edit] in detail window.

Item	Operation/Description
Edit Tasks	> Enter content
Due date	> Select how to enter due date → Enter due date ● Select No date to enter none.
Priority	> Select a priority level
Category	> Select a category
Alarm	> Select an Alarm type (→ For ON/Set time , enter time) ● Alarm Tone: ↪P.13-6
Alarm tone	> Select an Alarm tone type → Select a folder → Select an Alarm tone


- 2 [Finish]
 - When content is not entered, Tasks cannot be saved.

Note

- Alarm tone does not sound when Privacy Key Lock or Personal Data Lock is set. However, settings can be changed even while Personal Data Lock is set (↪P.12-6).

Using Tasks

In Tasks window, press  [Menu] for following operations.

Item	Operation/Description
New	Create a new entry (☞P.13-5)
Edit	Edit an entry (☞P.13-5)
Change status	Change status indicator shown in Tasks list > Select a status (→ for Completion , select an item → Enter Completion date) ● Overdue status indicator turns red.
Show by category	> Select a category
Sort/Filter	Sort list by due date, entry order, status, etc. > Select a condition
Add shortcut icon	Create a shortcut (☞P.1-25)
Send Ir data	(☞P.11-3)
Send all Ir data	(☞P.11-3)
IC transmission	(☞P.11-5)
AllIC transmission	(☞P.11-5)
Copy to microSD	Copy a Task to microSD Card > YES ● To display data on microSD Card: ☞P.10-20
Delete this	> YES
Delete select	> Check entries →  [Finish] → YES
Delete completed	Delete an entry in Completion status > YES
Delete all	> Enter Phone Password → YES

Alarms

Alarm Tone

When scheduled time arrives, alarm tone sounds and Notification Light illuminates.

- For Calendar events and Tasks, alarm message and animation corresponding to selected icon appear on Display.


To Stop Alarm Tone for Calendar Events, Tasks or Alarm

Press any key.

Missed Alarm

"Missed alarm" Event Indicator appears in Standby for alarms missed during Privacy Key Lock, Personal Data Lock or Infrared transmission once locks are canceled or transmission ends. Select indicator to view content.

Note

- When one or more Alarms are set to the same time, alarm sounds in the order of : "Alarm" → "Timer Recording" → "Tasks" → "Calendar" → "Timer Watching"
 For Tasks, "Missed alarm" indicator appears.
- If alarms are set for more than one Calendar event, press  [Next] when alarm sounds to toggle Calendar event entries.


Setting Alarm

Set up to 12 alarms. Alarm tone sounds at the specified time once, everyday or weekly as set.



-  appears in Standby when Alarm is set.

Main Menu ▶ Tools ▶ Alarms

1 Highlight an Alarm →  [Edit]



2 Select an item (See below)

Item	Operation/Description
Alarm	Activate or cancel Alarm > ON or OFF
Time	> Set Alarm time
Repeat	> Select a repeat type (→ For Select day , check days →  [Finish])
Tone	> Select an Alarm tone type → Select a folder → Select an Alarm tone
Volume	>  to set Alarm tone volume
Snooze	When Snooze is set to ON , Alarm tone sounds for 60 seconds, repeating up to six times at five minute intervals. > ON or OFF (→ For OFF , enter time)
Prefer manner mode	Set Manner Mode or Alarm priority. > ON or OFF



3 [Finish]

Alarm Indicators

- Following indicators appear:

 : Repeats daily  : Repeats weekly

Cancel & Reactivate Alarm

- > In Step 1 (highlight an Alarm),  [Menu] → Select an item → **YES**
- Cancel or reactivate an alarm entry as required.
- Highlight an entry →  to reactivate/cancel Alarm.

Snooze Function

If **ON**, press any key; Snooze window appears. To cancel Alarm, press .

Note


- Alarm tone does not sound when Privacy Key Lock or Personal Data Lock is set. However, settings can be changed even while Personal Data Lock is set (☞P.12-6).

Calculator

- Calculates up to 10 digits.

Main Menu ► Tools ► Calculator


Operation	Assigned key
Number (0 - 9)	0 - 9
+	
-	
x	
÷	
=	
Decimal point	
%	
Clear	



13 Tools

Example:

-17+28.5=11.5



Notepad

Save up to 20 notes.

Saving a Note


Main Menu ► Tools ► Notepad

1 <Not Recorded>

- Select a saved note to view content.
 [Edit] to edit.


2 Enter text










- Up to 256 double-byte or 512 single-byte characters can be entered.



Notepads Window

Notepad Functions

In Notepad list window, press  [Menu] for following operations.

Item	Operation/Description
Edit	Edit a saved note
Compose message	Insert Notepad text to message ( From Step 2 on P.14-4)
Edit schedule	Copy a note to Schedule to create a Calendar event > Schedule → Save a new note ( From Step 2 on P.13-2)
Add shortcut icon	Create a shortcut ( P.1-25)
Send Ir data	( P.11-3)
Send all Ir data	( P.11-3)
IC transmission	( P.11-5)
AllIC transmission	( P.11-5)
Copy to microSD	Copy a note to microSD Card > YES <ul style="list-style-type: none">● To display data on microSD Card:  P.10-20
Notepad Info	Display entry date, latest modified date and category of note
Category	> Select a category <ul style="list-style-type: none">● When no category applies, select None.
Delete this	> YES
Delete selected	> Check notes →  [Finish] → YES
Delete all	> Enter Phone Password → YES

Osaifu-Keitai®

"Osaifu-Keitai®" is a range of IC Card-based services used by Osaifu-Keitai® compatible handsets. Make purchases using e-money or e-ticketing. Hold handset up to a reader/writer to pay for your purchase.

■ Osaifu-Keitai® Terms

Osaifu-Keitai®	A contactless IC Card technology to read/write data by holding an IC card up to a reader/writer
IC Card	An IC chip embedded in Osaifu-Keitai®-compatible handsets
Lifestyle-Appli	Applications to use Osaifu-Keitai®. Some applications are preinstalled.

Precautions

- Data saved in IC Card vary by service content and usage history. Procedures to delete IC Card data vary by Lifestyle-Appli. Contact Osaifu-Keitai® service providers for details.
- SoftBank is not liable for damages from accidental loss or alteration of IC Card data or settings.
- IC Card data can be misused if your Osaifu-Keitai® compatible handset is lost or stolen. SoftBank is not liable for any resulting damages.
- Downloading Lifestyle-Appli and using applications may incur high packet transmission charges.

Getting Started

Downloading Lifestyle-Appli

Download Lifestyle-Appli via Internet website.

Registration/Settings

Activate Lifestyle-Appli to complete registration or customize settings.

- Make deposit into account, check payment records or balance, etc.

Note

- Keep a copy of service passwords/customer service contact, etc. in a separate place.

Downloading Lifestyle-Appli


Main Menu ► Tools ► Osaifu-Keitai ► Lifestyle-Appli

- 1 **Download** → **YES**
- 2 Select a Lifestyle-Appli
 - Lifestyle-Appli is saved to Data Folder.

Activating Lifestyle-Appli

- Lifestyle-Appli cannot be activated during a call or while another S! Appli is active.

Main Menu ► Tools ► Osaifu-Keitai ► Lifestyle-Appli

- 1 Select a Lifestyle-Appli
- 2 To exit,  → **Stopped**

Note


- Alternatively, **Main Menu ► S! Appli ► Osaifu-Keitai ► Lifestyle-Appli**
or
Main Menu ► Data Folder ► Lifestyle-Appli

Reader/Writer Transactions


- Complete registration/settings and charge your account beforehand.
- There is no need to activate a Lifestyle-Appli during transaction.

1 Hold logo up to reader/writer

- When IC Card Notification Light is **ON**, Notification Light illuminates (☞P.18-10).
- Hold handset parallel to reader/writer. Try moving handset around if recognition is slow.
- Check scan result on reader/writer display.
- Osaifu-Keitai® can be used during a call or Internet transmission (May require extra time.).



Note

- Data may be unreadable if a metal object, etc. is between  logo and reader/writer.
- Even though Osaifu-Keitai® is available while handset is off, Lifestyle-Appli does not activate. However, if battery is left uncharged after warning tone sounds, Osaifu-Keitai® may become disabled. Charge battery beforehand.
- When handset is held up to reader/writer, handset may show a message or vibrate depending on service. S! Appli, Messaging or Internet may also activate automatically. To avoid such cases, set the functions not to activate during transactions (☞P.18-26).

Tip

Settings


- Disable Handset Response to Commands from Reader/Writer (☞P.18-26)

IC Card Lock

Activating IC Card Lock

<Default> OFF

- While set,  appears in Standby.

1 Press and hold  → Enter Phone Password

- Repeat the step as required to unlock.

Note

- Alternatively, **Main Menu** ► **Tools** ► **Osaifu-Keitai**
► **IC Card Settings** ► **IC Card Lock** or **Main Menu** ► **Settings**
► **Security** ► **IC Card Lock**

Remote Lock



<Default> OFF

- Save up to three phone numbers to enable Remote Lock.

Main Menu ► **Tools** ► **Osaifu-Keitai** ► **IC Card Settings**
► **Remote Lock**

1 Enter Phone Password → **ON**

2 Select an item (See below)

Item	Operation/Description
Numbers to Permit	Save numbers to activate Remote Lock > <Not Recorded> → Enter phone numbers →  [Return] • To save numbers from Phone Book/Incoming Call Logs or to use a payphone number:  [Menu] → Refer to or Payphone
# of Incoming Call	Specify the number of incoming calls for activating IC Card Lock > Enter a number

3  [Set]

Activating Remote Lock

- ① Call 941P from one of the specified numbers (Send Caller ID)
- ② Hang up after 941P receives the call
- ③ Repeat ①-② until specified number of incoming calls is reached (within three minutes)
 - After specified number of incoming calls, IC Card Lock is set and a message informs you IC Card Lock is activated.

Note

- When setting IC Card Lock, call 941P from the same specified phone number. Incoming calls from different phone numbers cannot be counted.
- Specified incoming calls may not be counted when Call Forwarding is active.
- Remote Lock is not available when ring time for Answer Phone is set to 0 or Driving Mode is active.
- When Answer Phone activates, counted number of incoming calls are reset.

Dictionary (Japanese)

Use **ケータイTOOL<辞書>** to access dictionaries (学研 辞スバ英和・和英辞書 and 学研 国語辞書).

- ケータイTOOL<辞書> is an S! Appli.

Main Menu ▶ Tools ▶ Dictionary



1 Read **免責** (disclaimer) → **OK**

ケータイTOOL<辞書> activates.

- To disable **免責**:
Uncheck **アプリ起動時に常に表示する**。(Always show disclaimer when accessing dictionaries)

2 → Enter a word

Search results appear.


- To scroll pages: 
- To switch dictionaries: (1)/(3)
(In Horizontal Open Position: (1)/(7))
- To search again: [戻る]
(In Horizontal Open Position: (✳))

3 Select a word

Definition appears.

4 To end, → **Stopped**

Note

- While Dictionary application is active, press [メニュー] for useful functions.
- Word search is available while composing messages or viewing sent/received messages or website contents (☞P.14-8, P14-23, P.15-13).

Sound Recorders

Voice Recorder

Set recorded sounds for ringtones.

- Record for about 60 seconds each.

Main Menu ► Tools ► Sound Recorders ► Voice Recorder

1 **YES**

Recording starts.

2 [Stop] / (→ **OK**) to stop recording

Recorded sounds are saved in Ring Songs&Tones folder.

Voice Announce

Set recorded sound for on hold tone/holding tone, Alarm, Calendar event alarm, Tasks alarm, ringtones, Answer Phone message, Timer Watching (Digital TV), Ring Songs&Tones Play List.

- Record only one item for about 15 seconds.
- Select **Voice Announce** in individual window to set Voice Announce as specific tone.

Main Menu ► Tools ► Sound Recorders ► Voice Announce

1 **Record**

Recording starts.

Tone beeps five seconds before recording ends.

2 [Stop] to end recording

Tone beeps twice and previous screen returns.

- To play back: **Play**
- To delete: **Erase** → **YES**

Bar Code Reader

Scan barcodes (JAN) or QR Codes with built-in camera.
Access websites, send messages, etc. from QR Codes.

JAN Codes

JAN Code is a one-dimensional bar code denoting numerals with bars and spaces of different widths.

QR Codes

QR Code is a two-dimensional bar code containing information.

Example: SoftBank mobile phones



Scanning Barcodes

- Up to five items can be saved.
- For split data, up to 16 QR Codes can be scanned at a time and saved as one item.

Main Menu ▶ Tools ▶ Bar Code Reader ▶ Scan Barcodes

- 1 Frame barcode in the center of Display
 - To adjust Display brightness: [Menu] → **Brightness** → Adjust to -3 (dark) - +3 (light)
 - To zoom:
 - To use Focus Lock:

2 [Start]

Scanning starts, and scanned results appear when completed.

- For split data, **OK** → Repeat Step 1 and 2
- To use scanned data: Step 2 on P.13-16

3 [Menu] → **Save result** → **OK**

- To start over: → **YES**

Note

- Handset cannot read barcodes or two-dimensional codes other than JAN/QR Codes.
- Some barcodes may be unreadable.
- Barcode recognition may be slow. Hold handset steady while scanning.
- Barcodes may not be correctly read owing to scratch, dirt, damage, quality of printed material, light reflection, or QR code version.

Viewing/Editing Scanned Data

Main Menu ► Tools ► Bar Code Reader ► Saved Data List

- View**
Select an item

Edit Title


Highlight an item →  [Menu] → **Edit title** → Edit


Delete Saved Data

- > In Step 1, (highlight an item →)  [Menu] → **Delete** → **Delete this** or **Delete all** (→ For **Delete all**, enter Phone Password) → **YES**

Using Scanned Data

Main Menu ► Tools ► Bar Code Reader ► Saved Data List

- Select an item
-  [Menu] → Select an item (See below)

Item	Operation/Description
Save result	Save scanned results
Display list	Display Saved Data List
Internet	Access website > Yahoo! Keitai or PC Site Browser → YES ● Alternatively, select the URL.
Compose message	Insert address to message recipient field (↪ From Step 4 on P.14-4) ● Alternatively, select the address.
Dialing	Call selected phone number > Select a dialing method → Dial ● Alternatively, select phone number to dial.
Add to Phone Book	Save scanned results to Phone Book (↪ From Step 2 on P. 4-5)
Add bookmark	Save URL to Bookmark > YES →  [OK]
Copy	Copy selected characters to another place (↪ From Step 2 on P.3-10)