


Using Micro USB Cable (Mac)	4-2
Device Recognition (Mac)	4-2
Software Installation (Mac)	4-2
Connecting to Internet	4-4
Device Removal (Mac).....	4-5

Device Recognition (Mac)

Make sure USIM Card is installed in Wi-Fi router, insert Micro USB Cable plug into Wi-Fi router External Device Port. Insert Micro USB Cable plug into Mac USB port. Mac should automatically recognize Wi-Fi router within a few seconds.



See "Software Installation (Mac)" (P.4-2)

- Wi-Fi router may fail if Mac enters sleep mode, etc. with it connected. Remove Wi-Fi router before leaving a Mac unattended, etc. Wi-Fi router may malfunction if connected before Mac starts/restarts. Remove Wi-Fi router before starting or restarting Mac.


Software Installation (Mac)

All screenshots and procedures based on Mac OS 10.6.

Driver installation

Wi-Fi router driver and SoftBank 006Z Utility are saved in advance. For initial activation, they are installed automatically.


- Do not remove Wi-Fi router during installation. May cause installation failure, system malfunction or other system errors.

- 1 Power on Mac and initiate Mac
- 2 Connect Wi-Fi router to Mac via Micro USB Cable
If  icon appears on desktop, double-click it. SoftBank 006Z Utility opens automatically.
- 3 Double-click **SoftBank 006Z Utility** to start installation.
Dialog box below appears. Click **Continue**



- If an older version of this software, etc. is already installed, uninstall it, then install SoftBank 006Z Utility.
- Make sure that only the latest Utility is installed before use.

4 Standard Install on Macintosh HD dialog box appears. Click **Install**




- "Macintosh HD" is hard disk name. It may vary.

5 Certification appears. Enter Name and Password and click **OK**



6 Installation starts


7 When dialog box below appears, click **Close**



8 Web browser activates and SoftBank 006Z Utility appears

- Restart Mac if it does not function correctly.

Uninstalling Driver

- 1 Click  to open Finder
- 2 Remove **SoftBank 006 Utility**
 - Double-click **Uninstall SoftBank 006Z Utility** in Macintosh HD/application folder.
- 3 Click **Uninstall**
- 4 Certification appears. Enter Name and Password and click **OK**
- 5 When uninstallation finishes, click **Close**
- 6 Restart Mac

- "Macintosh HD" is hard disk name. It may vary.

Connecting to Internet

- 1 **Wi-Fi router: Activate WAN Connection Mode**
 - WAN Connection Mode is set to Always On by default. Press CONNECT Key or connect Wi-Fi router to PC and use SoftBank 006Z Utility to change it to Manual. See "Internet Connectivity" (P.5-21).


Device Removal (Mac)



- Close SoftBank 006Z Utility before removing Wi-Fi router. Do not remove Wi-Fi router during transmissions.

Follow these steps below to remove Wi-Fi router from Mac. Wi-Fi router may be damaged if it is improperly removed.

1 Click  to open Finder

2 In Finder, click  beside SoftBank 006Z




- If Memory Card is installed, first click  card removal icon, then click  beside SoftBank 006Z.

3 Remove Wi-Fi router from Mac

In Finder, if the above icon does not appear, end SoftBank 006Z Utility and remove Wi-Fi router.

Device Recognition (Mac)

Make sure USIM Card is installed in Wi-Fi router, insert Micro USB Cable plug into Wi-Fi router External Device Port. Insert Micro USB Cable plug into Mac USB port. Mac should automatically recognize Wi-Fi router within a few seconds.



See "Software Installation (Mac)" (P.4-2)

- Wi-Fi router may fail if Mac enters sleep mode, etc. with it connected. Remove Wi-Fi router before leaving a Mac unattended, etc. Wi-Fi router may malfunction if connected before Mac starts/restarts. Remove Wi-Fi router before starting or restarting Mac.


Software Installation (Mac)

All screenshots and procedures based on Mac OS 10.6.

Driver installation

Wi-Fi router driver and SoftBank 006Z Utility are saved in advance. For initial activation, they are installed automatically.


- Do not remove Wi-Fi router during installation. May cause installation failure, system malfunction or other system errors.

- 1 Power on Mac and initiate Mac
- 2 Connect Wi-Fi router to Mac via Micro USB Cable
If  icon appears on desktop, double-click it. SoftBank 006Z Utility opens automatically.
- 3 Double-click **SoftBank 006Z Utility** to start installation.
Dialog box below appears. Click **Continue**



- If an older version of this software, etc. is already installed, uninstall it, then install SoftBank 006Z Utility.
- Make sure that only the latest Utility is installed before use.

4 Standard Install on Macintosh HD dialog box appears. Click **Install**




- "Macintosh HD" is hard disk name. It may vary.

5 Certification appears. Enter Name and Password and click **OK**



6 Installation starts


7 When dialog box below appears, click **Close**



8 Web browser activates and SoftBank 006Z Utility appears

- Restart Mac if it does not function correctly.

Uninstalling Driver

- 1 Click  to open Finder
- 2 Remove **SoftBank 006 Utility**
 - Double-click **Uninstall SoftBank 006Z Utility** in Macintosh HD/application folder.
- 3 Click **Uninstall**
- 4 Certification appears. Enter Name and Password and click **OK**
- 5 When uninstallation finishes, click **Close**
- 6 Restart Mac

- "Macintosh HD" is hard disk name. It may vary.

Connecting to Internet

- 1 **Wi-Fi router: Activate WAN Connection Mode**
 - WAN Connection Mode is set to Always On by default. Press CONNECT Key or connect Wi-Fi router to PC and use SoftBank 006Z Utility to change it to Manual. See "Internet Connectivity" (P.5-21).


Device Removal (Mac)



- Close SoftBank 006Z Utility before removing Wi-Fi router. Do not remove Wi-Fi router during transmissions.

Follow these steps below to remove Wi-Fi router from Mac. Wi-Fi router may be damaged if it is improperly removed.

1 Click  to open Finder

2 In Finder, click  beside SoftBank 006Z



- If Memory Card is installed, first click  card removal icon, then click  beside SoftBank 006Z.

3 Remove Wi-Fi router from Mac

In Finder, if the above icon does not appear, end SoftBank 006Z Utility and remove Wi-Fi router.